

## Inteligentna Elektronika

Ul. Raduńska 36A  
83-333 Chmielno

Tel.: +48 730 90 60 90

E-mail: info@centrumprojekcji.pl



**BARCO**

Nazwa

**TransForm XDS-400 Universal  
collaboration box for any four-channel 3D  
stereo display**

Cena

**0,00 zł**

Producent

**Barco**

## OPIS PRODUKTU

### I/O properties

All interfaces are dual link DVI-I

Analog I/O: 50-270 MHz pixel clock

Digital I/O: 50-280 MHz pixel clock

All interfaces have a Mini Din 3 stereo sync connector

### I/O limits

Horizontal resolution 1024-2560 pixels

Vertical output resolution 768-1600 pixels

Frame rate 24-120Hz

### Outputs 4

Maximum displays 8 (using Barco Overview OLS projection cubes)

### PiP inputs

up to 6

### Desktop inputs

As many as there are output channels slots pre-equipped

Each desktop input signal must have the same resolution as the output channel

### Cluster PC input

As many as there are output channels slots pre-equipped

Each cluster input signal must have the same resolution as the output channel (in this case the number of PiP inputs is limited to 11)

### Stereo support

Any PiP input can be an active stereo signal, including the Cluster PC input

All outputs can be set to active stereo, left mono or right mono

### Overlap support

Up to 100% horizontal and vertical

Overlap possible

### Software

XDS Control Center software v3 or higher needed

Power

110-220 V

800 W max

Dimensions

19" rack mountable

9U high

Keep 1U free space under and above unit for cabling